

# LF-FMR040YSIII

FMR\*YSIII non-SELV 1-driver with 4-output current | Constant Current - Non dimmable



#### **Product family features**

- Low THD<15%@full load
- Rated input voltage: 220-240Vac
- Ta: -30°C~+60°C
- Ripple current<5%
- Suitable for Class I light fixtures
- 5 years guarantee



## **Product family benefits**

- Output current adjustable via DIP switch in 4 shifts
- Super high efficiency
- Linear metal casing with 21mm housing height
- Long lifetime and high reliability
- Flicker free
- Non-SELV output

#### Typical applications

- For linear light and tri-proof light
- For office, commercial, decorative and retail lighting

#### **Product parameters**

- Output current 200/250/300/350mA
- Output power 9-40W
- Input voltage 198-264Vac

- Output voltage 40-130Vdc
- Efficiency 91%


1

## **Electrical data**


Input data			
Rated supply voltage	220 240V		
AC voltage range	198 264V		
Mains frequency	0/50/60Hz		
Input voltage DC	180 264V <sup>1)</sup>		
Power factor	≥0.95		
Efficiency in max. power	91% <sup>2)</sup>		
THD	≤15%		
Input current	0.30A Max		
Inrush current	32A <sup>3)</sup>		
Loading no. on circuit breaker 10 A (B)	13		
Loading no. on circuit breaker 10 A (C)	21		
Loading no. on circuit breaker 16 A (B)	21		
Loading no. on circuit breaker 16 A (C)	35		
Loading no. on circuit breaker 20 A (C)	43		
Loading no. on circuit breaker 20 A (C)	54		
Protective conductor current	≤0.7mA		
Output data			
Nominal output voltage	40 130V <sup>4)</sup>		
Nominal output current	200/250/300/350mA <sup>5)</sup>		
Default output current	350mA		
Current set	DIP switch (please see the DIP switch definition)		
Maximum output power	40W		
Nominal output power	9 40W		
Output ripple current (100 Hz)	<5%		
Flicker	Comply with IEEE Std 1789-2015		
CIE SVM	≤0.4		
IEC-Pst	≤1		
Output current tolerance	±5%		
Temperature tolerance	±10%		
Starting time	<0.5S		
Safety			
Withstanding voltage	I/P-PG: 1.6kV&5mA&60S;		
Surge capability (L-N)	1kV		
Surge capability (L/N-Ground)	2kV		
Insulation resistance	I/P-PG O/P-PG: >100MΩ@500VDC		
Guarantee	5 years <sup>6)</sup>		


- 1) DC input is only for emergency
- 2) @full load
- 3) t =190µs
- 4) Please refer to the operating window about the relationship between output voltage and output current.
- 5) Fixed current version optional
- 6) **5 years @Tc≤ 81** °C

## Characteristic diagram




#### Typical Efficiency vs Load 95 90 200mA Efficiency (%) 250mA 300mA 350mA 80 75 5 10 15 20 25 30 35 40 45 Output power (W)






## Lifespan



## **Dimensions**



Mounting hole spacing, length	158.0mm
Mounting hole diameter	4.2mm
Product weight	110.0g
Cable cross-section, input side	0.5 1.5 mm²
Cable cross-section, output side	0.5 1.5 mm²
Wire preparation length, input side	7 8mm
Wire preparation length, output side	7 8mm
Length	168.0mm
Width	30.0mm
Height	21.0mm


## **Colors & materials**

Casing material	Color coated galvanized sheet
Casing color	White

## Temperature & operating conditions

Ambient temperature range	-30°C - +60°C		
Maximum temperature at Tc test point	<b>85</b> ℃		
Temperature range at storage	-30°C - +80°C (6 months in Class I environment)		
Humidity range at storage	20-95%RH(no condensation)		
Humidity during operation	20-90%RH(no condensation)		
RoHS	RoHS 2.0 (EU) 2015/863		

# Tc test point



Note: this diagram is the front view and Tc point is on the front side of the driver.

#### **Product Terminal**

Input		Output	
AC-L	AC live wire input	LED+	Positive electrode output of LED driver
AC-N	AC neutral wire input	LED-	Negative electrode output of LED driver
	Earth wire		

## **DIP switch Terminal**

Output current	Output voltage	DIP switch 1	DIP switch 2
200mA	40-130Vdc	-	-
250mA	40-130Vdc	-	ON
300mA	40-130Vdc	ON	-
*350mA	40-115Vdc	ON	ON

Note: "-": shift OFF. "\*": default current. DIP when power on is NOT allowed. Please disconnect the AC power before DIP.

# Capabilities

Dimmable	-
Over heating protection	-
Overload protection	-
Short-circuit protection	Automatic reversible
No-load protection	<200V
Suitable for fixtures with prot. class	I
Control interface	-
Number of channels	1 channel

# **Programming**

Programmer	-
DALI Control Software	-
APP	-

## **Certificates & standards**

Approval marks	ENEC, UKCA, CE, CB, EL, RCM, SAA, EAC, CCC		
Standards	GB 19510.1-2009, GB 19510.14-2009		
	IEC/EN 61347-2-13, IEC/EN 61347-1, IEC/EN 62493		
	IEC/EN 62384		
	IEC/EN 61347-2-13 Annex J		
	AS 61347.1, AS 61347.2.13		
	TP TC 004/2011+TP TC 020/2011		
EMC	GB 17625.1-2022, GB/T 17743-2021		
	EN 55015, EN 61547, EN 61000-3-2,3		
Type of protection	IP20		

# **Logistical Data**

Product	Packaging unit (Pieces/Unit)	Dimensions (L*W*H)	Volume	Gross weight
LF-FMR040YSIII	84	385mm*285mm*210mm	23.04 dm³	9.85kg±5%

#### **Test equipment & condition**

# AC power source: CHROMA6530, digital power meter: CHROMA66205, oscilloscope: Tektronix DPO3014, DC electronic load: M9712B, LED board, constant temperature and humidity chamber, lightning surge generator: Everfine EMS61000-5B, rapid group pulse generator: Everfine EMS61000-4A, spectroanalyzer: KH3935, hi-pot tester: EEC SE7440, flicker tester (flicker-free coefficient test): Everfine LFA-3000, etc.

If there are no special remarks, the above parameters are tested at the ambient temperature of  $25^{\circ}$ C, humidity of 50%, maximum output power and input voltage of 230Vac/50Hz.

#### Additional information

- 1. It is recommended that user install the over voltage protection, under voltage protection and surge protection devices in the power supply circuits of light fixtures to ensure electricity safety.
- 2. The LED driver used in combination with the end device is one of the accessories of the whole light fixture, and the EMC of the whole light fixture is not only susceptible to the driver itself, but to the LED light fixture and the whole light fixture's wiring. Thus, the manufacturer of LED light fixture should re-confirm the EMC of the whole light fixture before the whole light fixture is finished.
  - 3. Configure the quantity of circuit breakers based on inrush current and time.
- 4. The PC cover, casing and end cap for assembling the LED driver in the light fixture must meet the fire rating of UL94-V0 or above.

#### **Transportation & storage**

Suitable transportation means: vehicles, boats and aeroplanes.

In transit, it is necessary to prepare awnings for rain or sun protection. Moreover, please keep civilized loading and unloading to prevent the vibration or impact of LED driver as much as possible.

The storage of LED driver shall conform to the standard of Class I environment. When using LED drivers which have been stored for more than 6 months, please re-test them firstly. Do not use them unless they are tested to be qualified.

#### **Cautions**

Please use Lifud LED driver according to its parameters in the specification, otherwise the LED driver may malfunction. Using any incompatible light fixtures or those that have not been certified may cause fire, explosion or other risks.

Man-made damage is beyond the scope of Lifud warranty service.

#### **Disclaimer**

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release. Lifud Technology Co., Ltd. reserves the right to interpret any contents of this specification.